



Allwinner A31/A31s NandFlash Support List

V1.0

2014-03-27



- Revision History

Revision No.	History	Date	Author
V1.0	1. Initial version build.	2014.03.27	Tony.Chow

- Note Introduction

Note	Description
SNT	Support but no sample test
SST	Support and sample test
√	Support and mass produce

- Attention

This support list is based on the latest nand flash driver version.



• Support List

VENDER	PART NUMBER	CELL	CEs	RBs	PAGE SIZE	BLOCK SIZE	CAPACITY	PROCESS	PACKAGE	NOTE
SANSUMG	K9K2G08U0(A/M)	SLC	1	1	2K+64	128K+4K	256M		TSOP	SST
	K9W4G08U0M	SLC	1	1	2K+64	128K+4K	512M		TSOP	SST
	K9W4G08U1M	SLC	2	2	2K+64	128K+4K	512M		TSOP	SST
	K9K4G08U0(A/M)	SLC	1	1	2K+64	128K+4K	512M		TSOP	SST
	K9F4G08U0(A/M)	SLC	1	1	2K+64	128K+4K	512M		TSOP	SST
	K9W8G08U1M	SLC	2	2	2K+64	128K+4K	1G		TSOP	SST
	K9K8G08U0(A/M)	SLC	1	1	2K+64	128K+4K	1G		TSOP	SST
	K9K8G08U1M	SLC	2	2	2K+64	128K+4K	1G		TSOP	SST
	K9WAG08U0(A/M)	SLC	1	1	2K+64	128K+4K	2G		TSOP	SST
	K9WAG08U1(A/M)	SLC	2	2	2K+64	128K+4K	2G		TSOP	SST
	K9F8G08U0(A/M)	SLC	1	1	4K+128	256K+8K	1G		TSOP	SST
	K9KAG08U0M	SLC	1	1	4K+128	256K+8K	2G		TSOP	SST
	K9F1G08U0(A/B/M)	SLC	1	1	2K+64	128K+4K	128M		TSOP	SST
	K9F2G08U0(A/M)	SLC	1	1	2K+64	128K+4K	256M		TSOP	SST
	K9G4G08U0(A/M)	MLC	1	1	2K+64	256K+8K	512M		TSOP	SST
	K9L8G08U0M	MLC	1	1	2K+64	256K+8K	1G		TSOP	SST
	K9G8G08U0M	MLC	1	1	2K+64	256K+8K	1G		TSOP	SST
	K9LAG08U0M	MLC	1	1	2K+64	256K+8K	2G		TSOP	SST
	K9GAG08U0M/D	MLC	1	1	4K+128	512K+16K	2G		TSOP	SST
	K9LBG08U0M/D	MLC	1	1	4K+128	512K+16K	4G		TSOP	SST
K9HBG08U1M	MLC	2	2	2K+64	256K+8K	4G		TSOP	SST	



VENDER	PART NUMBER	CELL	CEs	RBs	PAGE SIZE	BLOCK SIZE	CAPACITY	PROCESS	PACKAGE	Note
SANSUMG	K9HCG08U0M	MLC	1	1	4K+128	512K+16K	8G		TSOP	SST
	K9HCG08U1M	MLC	2	2	4k+128	512K+16K	8G		TSOP	SST
	K9GBG08X0M	MLC	1	1	8K+436	1M+54.5K	4G	32nm	TSOP	SST
	K9GAG08U0E	MLC	1	1	8K+436	1M+54.5K	2G	32nm	TSOP	SST
	K9G8G08U0C	MLC	1	1	8K+436	1M+54.5K	1G		TSOP	SST
	K9GBG08U0A	MLC	1	1	8K+640	1M+60K	4G	27nm	TSOP	√
	K9GBGD8U0A	MLC	1	1	8K+640	1M+60K	4G	27nm	LGA	√
	K9GBG08U0B	MLC	1	1	8K+1K	1M+128K	4G	21nm	TSOP	√
	K9LCG08U0A	MLC	1	1	8K+640	1M+80K	8G	27nm	TSOP	√
	K9HDG08U1A	MLC	2	2	8K+640	1M+80K	16G	27nm	TSOP	√
	K9LCG08U0B	MLC	1	1	8K+1K	1M+128K	8G	21nm	TSOP	√
HYNIX	HY27UF081G2(A/M)	SLC	1	1	2K+64	128K+4K	128M		TSOP	SST
	HY27UF082G2(A/M)	SLC	1	1	2K+64	128K+4K	256M		TSOP	SST
	HY27UH084G2M	SLC	1	1	2K+64	128K+4K	512M		TSOP	SST
	HY27UF084G2M	SLC	1	1	2K+64	128K+4K	512M		TSOP	SST
	HY27UG084G2M	SLC	1	1	2K+64	128K+4K	512M		TSOP	SST
	HY27UF084G2B	SLC	1	1	2K+64	128K+4K	512M		TSOP	SST
	HY27UG088G5M	SLC	2	2	2K+64	128K+4K	1G		TSOP	SST
	HY27UG088G5B	SLC	2	2	2K+64	128K+4K	1G		TSOP	SST
	HY27H088G2M	SLC	1	1	2K+64	128K+4K	1G		TSOP	SST
	HY27UG088G2M	SLC	1	1	2K+64	128K+4K	1G		TSOP	SST
	HY27UH08AG5M	SLC	2	2	2K+64	128K+4K	2G		TSOP	SST
HY27U4G8T2BTR	SLC	1	1	2K+64	128K+4K	512M		TSOP	SST	



VENDER	PART NUMBER	CELL	CEs	RBs	PAGE SIZE	BLOCK SIZE	CAPACITY	PROCESS	PACKAGE	Note
HYNIX	H27U1G8F2B	SLC	1	1	2K+64	128K+4K	128M		TSOP	SST
	HY27UF082G2B	SLC	1	1	2K+64	128K+4K	256M		TSOP	SST
	HY27UT084G2M	MLC	1	1	2K+64	256K+8K	512M		TSOP	SST
	HY27UU088G5M	MLC	2	2	2K+64	256K+8K	1G		TSOP	SST
	HY27UT088G2M	MLC	1	1	2K+64	256K+8K	1G		TSOP	SST
	HY27UT088G2M	MLC	1	1	2K+64	256K+8K	1G		TSOP	SST
	HY27UT088G2M	MLC	1	1	2K+64	256K+8K	1G		TSOP	SST
	HY27UV08AG5M	MLC	2	2	2K+64	256K+8K	2G		TSOP	SST
	HY27UU08AG5M	MLC	2	2	2K+64	256K+8K	2G		TSOP	SST
	HY27UU08AG5M	MLC	2	2	2K+64	256K+8K	2G		TSOP	SST
	HY27UU08AG5M	MLC	2	2	2K+64	256K+8K	2G		TSOP	SST
	H27UAG8T2A	MLC	1	1	4K+128	512K+16K	2G		TSOP	SST
	HY27UV08BG5M	MLC	2	2	2K+64	256K+8K	4G		TSOP	SST
	HY27UV08BG5M	MLC	2	2	2K+64	256K+8K	4G		TSOP	SST
	HY27UV08BG5M	MLC	2	2	2K+64	256K+8K	4G		TSOP	SST
	H27UBG8U5A	MLC	2	2	4K+224	512K+28K	4G		TSOP	SST
	H27UCG8V5M	MLC	2	2	4K+128	512K+16K	8G		TSOP	SST
	H27UCG8V5A	MLC	2	2	4K+224	512K+28K	8G	32nm	TSOP	SST
	H27UBG8T2A	MLC	1	1	8K+448	2M+112K	4G	32nm	TSOP	SST
	H27UCG8U5(D)A	MLC	2	2	8K+448	2M+112K	8G	32nm	TSOP	SST
	H27UDG8V5A	MLC	2	2	8K+448	2M+112K	16G	32nm	TSOP	SST
	H27UBG8T2M	MLC	1	1	4K+224	512K+28K	4G		TSOP	SST
H27UAG8T2B	MLC	1	1	8K+448	2M+112K	2G	32nm	TSOP	SST	
H27U8G8T2B	MLC	1	1	4K+128	512K+16K	1G		TSOP	SST	



VENDER	PART NUMBER	CELL	CEs	RBs	PAGE SIZE	BLOCK SIZE	CAPACITY	PROCESS	PACKAGE	Note
HYNIX	H27UBG8T2BTR	MLC	1	1	8K+448	2M+112K	4G	26nm	TSOP	SST
	H27UCG8U5BTR	MLC	2	2	8K+448	2M+112K	8G	26nm	TSOP	SST
	H27UCG8T2MYR	MLC	1	1	8K+448	2M+112K	8G	26nm	LGA	√
	H27UBG8T2CTR	MLC	1	1	8K+640	2M+160K	4G	20nm	TSOP	√
	H27UCG8T2ATR	MLC	1	1	8K+640	2M+160K	8G	20nm	TSOP	√
	H27UCG8T2BYR	MLC	1	1	16K+1280	4M+320K	8G	20nm	LGA	√
	H27UCG8T2BTR	MLC	1	1	16K+1280	4M+320K	8G	20nm	TSOP	√
	H27UCG8T2ETR	MLC	1	1	16K+1664	4M+416K	8G	16nm	TSOP	SST
MICRON	MT29F2G08AAC	SLC	1	1	2K+64	128K+4K	256M		TSOP	SST
	MT29F4G08BAB	SLC	1	1	2K+64	128K+4K	512M		TSOP	SST
	MT29F4G08AAA	SLC	1	1	2K+64	128K+4K	512M		TSOP	SST
	MT29F8G08FAB	SLC	2	2	2K+64	128K+4K	1G		TSOP	SST
	MT29F8G08DAA	SLC	2	2	2K+64	128K+4K	1G		TSOP	SST
	MT29F8G08BAB	SLC	1	1	2K+64	128K+4K	1G		TSOP	SST
	MT29F16G08FAB	SLC	2	2	2K+64	128K+4K	2G		TSOP	SST
	MT29F4G08MAA	MLC	1	1	2K+64	256K+8K	512M		TSOP	SST
	MT29F8G08QAA	MLC	2	2	2K+64	256K+8K	1G		TSOP	SST
	MT29F8G08MAA	MLC	1	1	2K+64	256K+8K	1G		TSOP	SST
	MT29F16GTAA	MLC	2	2	2K+64	256K+8K	2G		TSOP	SST
	MT29F16G08QAA	MLC	2	2	2K+64	256K+8K	2G		TSOP	SST
	MT29F32G08TAA	MLC	2	2	2K+64	256K+8K	4G		TSOP	SST
	MT29F32G08TAA	MLC	2	2	2K+64	256K+8K	4G		TSOP	SST
	MT29F32G08CBAAA	MLC	1	1	4K+218	512K+27K	4G	34nm	TSOP	SST
	MT29F32G08CBABA	MLC	1	1	4K+224	1024K+56K	4G	34nm	TSOP	SST



VENDER	PART NUMBER	CELL	CEs	RBs	PAGE SIZE	BLOCK SIZE	CAPACITY	PROCESS	PACKAGE	Note
MICRON	MT29F64G08TAA	MLC	2	2	4K+128	512K+16K	8G	34nm	TSOP	SST
	MT29F64G08CFAAA	MLC	2	2	4K+218	512K+27K	8G	34nm	TSOP	SST
	MT29F128G08CJAAA	MLC	2	2	4K+218	512k+27K	16G	34nm	TSOP	SST
	MT29F128G08CJABA	MLC	2	2	4K+218	512k+27K	16G	34nm	TSOP	SST
	MT29F64G08CBAAA	MLC	1	1	8K+448	2M+112K	8G	25nm	TSOP	√
	MT29F32G08CBACA	MLC	1	1	4K+224	1M+56K	4G	25nm	TSOP	√
	MT29F16G08CBABA	MLC	1	1	4K+224	1M+56K	2G	34nm	TSOP	SST
	MT29F16G08CBACA	MLC	1	1	4K+224	1M+56K	2G	25nm	TSOP	SST
	MT29F128G08CFAAA	MLC	2	2	8K+448	2M+112K	16G	25nm	TSOP	SST
	MT29F64G08CBABA	MLC	1	1	8K+744	2M+186K	8G	20nm	TSOP	√
	MT29F32G08CBADA	MLC	1	1	8K+744	2M+186K	4G	20nm	TSOP	√
INTEL	JS29F02G08AAN	SLC	1	1	2K+64	128K+4K	256M		TSOP	SST
	JS29F04G08BAN	SLC	1	1	2K+64	128K+4K	512M		TSOP	SST
	JS29F04G08AAN	SLC	1	1	2K+64	128K+4K	512M		TSOP	SST
	JS29F08G08FAN	SLC	1	1	2K+64	128K+4K	1G		TSOP	SST
	JS29F08G08BAN	SLC	1	1	2K+64	128K+4K	1G		TSOP	SST
	JS29F16G08FAN	SLC	2	2	2K+64	128K+4K	2G		TSOP	SST
	JS29F08G08AAM	MLC	1	1	2K+64	256K+8K	1G		TSOP	SST
	JS29F16G08CAM	MLC	2	1	2K+64	256K+8K	2G		TSOP	SST
	JS29F32G08FAM	MLC	2	2	2K+64	256K+8K	4G		TSOP	SST
	JS29F32G08FAM	MLC	2	2	2K+64	256K+8K	4G		TSOP	SST
	JS29F32G08AAMD2	MLC	1	1	4K+218	512K+27K	4G		TSOP	SST
	JS29F32G08CAMC1	MLC	2	2	4K+218	512K+27K	4G		TSOP	SST
JS29F64G08CAMD2	MLC	2	2	4K+218	512K+27K	8G		TSOP	SST	



VENDER	PART NUMBER	CELL	CEs	RBs	PAGE SIZE	BLOCK SIZE	CAPACITY	PROCESS	PACKAGE	Note
INTEL	JS29F32G08AAMDB	MLC	1	1	4K+224	1M+56K	4G	34nm	TSOP	SST
	JS29F64G08FAMC1	MLC	2	2	4K+218	512K+27K	8G	34nm	TSOP	SST
	JS29F64G08CAMDB	MLC	2	2	4K+224	1M+56K	8G	34nm	TSOP	SST
	JS29F64G08AAME1	MLC	1	1	8K+448	2M+112K	8G	25nm	TSOP	SST
	JS29F64G08ACME3	MLC	1	1	8K+448	2M+112K	8G	25nm	TSOP	SST
	JS29F16B08CCME3	MLC	2	2	8K+448	2M+112K	16G	25nm	TSOP	SST
	JS29F32B08JCME3	MLC	4	4	8K+448	2M+112K	32G	25nm	TSOP	SST
	JS29F64G08ACMF3	MLC	1	1	8K+744	2M+186K	8G	20nm	TSOP	SST
	JS29F16B08CCMF3	MLC	2	2	8K+744	2M+186K	16G	20nm	TSOP	SST
JS29F32B08JCMF3	MLC	4	4	8K+744	2M+186K	32G	20nm	TSOP	SST	
SANDISK	SDTNQGAMA-008G	MLC	1	1	16k+1280	4M+320K	8G	19nm	TSOP	√
	SDTNQFAMA-004G	MLC	1	1	16k+1280	4M+320K	4G	19nm	TSOP	√
	SDTNRGAMA-008G	MLC	1	1	16k+1280	4M+320K	8G	A19nm	TSOP	SST
	SDTNQGAMA-008GP	MLC	1	1	16k+1280	4M+320K	8G	A19nm	TSOP	SST
TOSHIBA	TC58NVG0S3ETA00	SLC	1	1	2K+64	128K+4K	128M		TSOP	SST
	TH58NVG6D1DTH20	MLC	2	2	4K+224	512K+27K	8G		TSOP	SST
	TH58NVG5D1DTG20	MLC	2	2	4K+218	512K+27K	4G		TSOP	SST
	TC58NVG4D2FTA00	MLC	1	1	8K+448	1M+56K	2G		TSOP	SST
	TC58NVG5D2FTA00	MLC	1	1	8K+448	1M+56K	4G		TSOP	SST
	TC58NVG6D2FTA20	MLC	2	2	8K+448	1M+56K	8G		TSOP	SST
	TC58NVG4D2HTA00	MLC	1	1	8K+640	1M+80K	2G	24nm	TSOP	SST
	TC58NVG5D2HTA00	MLC	1	1	8K+640	1M+80K	4G	24nm	TSOP	SST
	TC58NVG6D2GTA00	MLC	1	1	8K+640	1M+80K	8G	24nm	TSOP	SST
	TH58NVG7D2GTA20	MLC	2	2	8K+640	1M+80K	16G	24nm	TSOP	SST



VENDER	PART NUMBER	CELL	CEs	RBs	PAGE SIZE	BLOCK SIZE	CAPACITY	PROCESS	PACKAGE	Note
TOSHIBA	TC58TEG5DCJTA00	MLC	1	1	16K+1280	4M+320K	4G	19nm	TSOP	SST
	TC58NVG6DCJTA00	MLC	1	1	16K+1280	4M+320K	8G	19nm	TSOP	√
	TC58TEG6DCJTA00	MLC	1	1	16K+1280	4M+320K	8G	19nm	TSOP	√
	TC58TEG6DDJTA00	MLC	1	1	16K+1280	4M+320K	8G	19nm	TSOP	SST
	TH58TEG7DCJTA20	MLC	2	2	16K+1280	4M+320K	16G	19nm	TSOP	SST
	TH58TEG7DDKTA20	MLC	2	2	16K+1280	4M+320K	16G	19nm	TSOP	SST
	TC58TEG6DDKTA00	MLC	1	1	16K+1280	4M+320K	8G	19nm	TSOP	SST



- **Declaration**

This document is the original work and copyrighted property of Allwinner Technology (“Allwinner”). Reproduction in whole or in part must obtain the written approval of Allwinner and give clear acknowledgement to the copyright owner.

The information furnished by Allwinner is believed to be accurate and reliable. Allwinner reserves the right to make changes in circuit design and/or specifications at any time without notice. Allwinner does not assume any responsibility and liability for its use. Nor for any infringements of patents or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of Allwinner. This datasheet neither states nor implies warranty of any kind, including fitness for any particular application.